# Russellstoll<sup>®</sup>

## **Heavy Duty Tumbler Switches**

General use heavy duty switches are applied to control a variety of lighting, power and machinery branch circuit loads. They can be used with any Russellstoll industrial receptacle for maximum control system flexibility.

### **Ordering Information**



#### 1-2 HP Rated

Switch	125/250 V Hp	AC Rating Amps	Cast Aluminum	Cast Brass
Single Pole / Single Throw	1.5/2.0	15	3705S7	3725\$7
	1.0/2.0	20	3705S27	3725S27
	2.0/2.0	30	3705S37	3725S37
Double Pole / Single Throw	1.5/2.0	15	3706D7	3726D7
	1.0/2.0	20	3706D27	3726D27
	2.0/2.0*	30	3706D37	3726D37

#### Notes:

Switches rated 15 or 20 Amp. 277 volts, A.C. and with other than listed ratings can be furnished. Prices and information on application. AC only.

Boxes Available in cast aluminum, cat. no. 3701A and cast brass cat. no. 3721.

# **Specifications**


**Enclosures** – Corrosion resisting baked enamel finish. Cast brass, natural finish.

**Gang Types** – Can be furnished in 2 gang aluminum or tandem units and in combination with other Russellstoll FS and FD devices. Contact Technical Services.

**Outlets** – Unless otherwise specified, furnished with one ¾" outlet per gang, top or bottom. Additional or larger outlets charged extra – see price list. Maximum conduit 1": single gang – top and bottom only, multiple gang – one per gang top and bottom and one each side. Specify size and location.

**Flush Mounting** – Adapters for flush mounting are listed on page H121.

#### **Dimensions**





<sup>\*</sup> Also rated 1 Hp, 460VAC or 2Hp to 600VAC.